







Marco	Rango de Ajuste (A)	Vn (V)	Vi (V)	Icu (KA)					SERIE H	Icu (KA)					SERIE R	Icu (KA)					
				SERIE S	A02Z	A08E	A0H4	A0S5		A0G9	A02Z	A08E	A0H4	A0S5		A0G9	A02Z	A08E	A0H4	A0S5	A0G9
Frecuencia (Hz)				50/60					50/60					50/60							
Nº Pólos				3					3					3							
	125	690	800	SD-S10					SD-H10						-						
				SD-S16					SD-H16							-					
				SD-S20					SD-H20							-					
				SD-S25					SD-H25							-					
				SD-S32					SD-H32							-					
				SD-S40	42	25	20	10	3	SD-H40	65	50	42	25	8	-	-	-	-	-	-
				SD-S50						SD-H50						-					
				SD-S63						SD-H63						-					
				SD-S70						-						-					
				SD-S80						SD-H80						-					
				SD-S100						SD-H100						-					
	SD-S125						SD-H125						-								
	250	690	800	SD-S150					-					-							
				SD-S160					SD-H160						SD-R160						
				SD-S175					SD-H175						-						
				SD-S180	42	25	20	10	5	SD-H180	65	50	42	25	8	-	85	65	55	35	10
				SD-S200						SD-H200						SD-R200					
				SD-S225						SD-H225						-					
				SDD-S250						SD-H250						SDD-R250					
																-					
																-					
																-					
	400	690	800	SDD-S300					-					-							
				SDD-S315	50	35	30	15	10	SDD-H315	85	50	42	25	12	SDD-R315	100	70	65	42	15
				SDD-S350						SDD-H350						SDD-R350					
				SDD-S400						SDD-H400						SDD-R400					
																-					
	630	690	800	SDD-S450					-					-							
				SDD-S500	50	35	30	15	12	SDD-H500	85	50	42	25	13	SDD-R500	100	70	65	40	20
				SDD-S600						-					-						
				SDD-S630						SDD-H630						SDD-R630					
																-					
	800	690	800	-					SDD-H700	85	60	55	30	15	SDD-R700	100	70	65	40	20	
				-					SDD-H800						SDD-R800						
	1250	690	800	-					SDD-H1000	85	65	55	25	15	-						
				-					SDD-H1200						-						