



	Corriente Nominal de empleo		Rango de tensión de mando		Contactos auxiliares incorporados		Tipo	Código	Peso Unitario (kgs)
	400 V ca AC-3 A	690 V ca AC-1 A	Uc mín. ... Uc máx.		1	2			
			V ca 50/60 Hz	V cd					
 Tamaño 1	9	25	24...60	20...60	1	0	AF09Z-30-10-21	<b>1SBL136001R2110</b>	0.310
			24...60	20...60	0	1	AF09Z-30-01-21	<b>1SBL136001R2101</b>	0.310
			48...130	48...130	1	0	AF09-30-10-12	<b>1SBL137001R1210</b>	0.270
			48...130	48...130	0	1	AF09-30-01-12	<b>1SBL137001R1201</b>	0.270
			100...250	100...250	1	0	AF09-30-10-13	<b>1SBL137001R1310</b>	0.270
			100...250	100...250	0	1	AF09-30-01-13	<b>1SBL137001R1301</b>	0.270
	12	28	250...500	250...500	1	0	AF09-30-10-14	<b>1SBL137001R1410</b>	0.310
			250...500	250...500	0	1	AF09-30-01-14	<b>1SBL137001R1401</b>	0.310
			24...60	20...60	1	0	AF12Z-30-10-21	<b>1SBL156001R2110</b>	0.310
			24...60	20...60	0	1	AF12Z-30-01-21	<b>1SBL156001R2101</b>	0.310
			48...130	48...130	1	0	AF12-30-10-12	<b>1SBL157001R1210</b>	0.270
			48...130	48...130	0	1	AF12-30-01-12	<b>1SBL157001R1201</b>	0.270
	18	30	100...250	100...250	1	0	AF12-30-10-13	<b>1SBL157001R1310</b>	0.270
			100...250	100...250	0	1	AF12-30-01-13	<b>1SBL157001R1301</b>	0.270
			250...500	250...500	1	0	AF12-30-10-14	<b>1SBL157001R1410</b>	0.310
			250...500	250...500	0	1	AF12-30-01-14	<b>1SBL157001R1401</b>	0.310
			24...60	20...60	1	0	AF16Z-30-10-21	<b>1SBL176001R2110</b>	0.310
			24...60	20...60	0	1	AF16Z-30-01-21	<b>1SBL176001R2101</b>	0.310
 Tamaño 2	26	45	48...130	48...130	1	0	AF16-30-10-12	<b>1SBL177001R1210</b>	0.270
			48...130	48...130	0	1	AF16-30-01-12	<b>1SBL177001R1201</b>	0.270
			100...250	100...250	1	0	AF16-30-10-13	<b>1SBL177001R1310</b>	0.270
			100...250	100...250	0	1	AF16-30-01-13	<b>1SBL177001R1301</b>	0.270
	32	50	250...500	250...500	1	0	AF16-30-10-14	<b>1SBL177001R1410</b>	0.310
			250...500	250...500	0	1	AF16-30-01-14	<b>1SBL177001R1401</b>	0.310
			24...60	20...60	0	0	AF26Z-30-00-21	<b>1SBL236001R2100</b>	0.350
			48...130	48...130	0	0	AF26-30-00-12	<b>1SBL237001R1200</b>	0.310
	38	50	100...250	100...250	0	0	AF26-30-00-13	<b>1SBL237001R1300</b>	0.310
			250...500	250...500	0	0	AF26-30-00-14	<b>1SBL237001R1400</b>	0.350
			24...60	20...60	0	0	AF30Z-30-00-21	<b>1SBL276001R2100</b>	0.350
			48...130	48...130	0	0	AF30-30-00-12	<b>1SBL277001R1200</b>	0.310
38	50	100...250	100...250	0	0	AF30-30-00-13	<b>1SBL277001R1300</b>	0.310	
		250...500	250...500	0	0	AF30-30-00-14	<b>1SBL277001R1400</b>	0.350	
		24...60	20...60	0	0	AF38Z-30-00-21	<b>1SBL296001R2100</b>	0.350	
		48...130	48...130	0	0	AF38-30-00-12	<b>1SBL297001R1200</b>	0.310	
38	50	100...250	100...250	0	0	AF38-30-00-13	<b>1SBL297001R1300</b>	0.310	
		250...500	250...500	0	0	AF38-30-00-14	<b>1SBL297001R1400</b>	0.350	

Dimensiones principales mm, pulgadas

AF09, AF12, AF16

AF26, AF30, AF38

